6.3000: Signal Processing

Systems

Linearity and Time Invariance

Determine which of the following systems are linear.

Determine which of the following systems are time-invariant.

- 1. y[n] = x[-n]
- 2. y[n] = x[2n]
- $3. \ y[n] = \Big| x[n] \Big|$

Linearity and Time Invariance

Determine which of the following systems are linear.

Determine which of the following systems are time-invariant.

4.
$$y(t) = \frac{d}{dt}x(t)$$

5.
$$y(t) = \int_0^t x(\tau)d\tau$$

6.
$$y(t) = \int_{-\infty}^{t} x(\tau)d\tau$$

7.
$$y(t) = \int_{t}^{\infty} x(\tau)d\tau$$

8.
$$y(t) = \int_{-\infty}^{\infty} x(\tau)d\tau$$